

StarFire 6000™ Receiver Software Reprogramming

Preparing Starfire™ 6000 Receiver Software for a USB At Computer

1. Download the new software and save the .zip file to your computer (desktop).
2. Select the file that is now on your desktop and extract the data (this is the same as unzip) to your desktop.
3. Using a USB storage device, a specific file structure will need to be created. (Note - the folder names will need to be in the English Language)
 - a. First create a folder and title it “Programs”
 - b. Create a secondary folder within the “Programs” folder titled “Receiver”
4. Copy the extracted file to the USB storage device file structure - Programs > Receiver
 - a. Verify that you have a .prc file on our USB storage device within the receiver folder. If you have a .prc file in the receiver folder the software is now ready to be installed.

At Machine with StarFire™ 6000 Universal Receiver

1. Identify the StarFire™ 6000 USB port on the bottom of the receiver.
2. Insert your USB with the correct .prc file embedded and proceed to the display within the cab to initiate download.
3. At the display, follow the steps below to initiate the programming of the StarFire™ 6000:
 - a. Select “Main Menu”
 - b. Select “StarFire™ 6000” icon
 - c. Select “USB Drive” (softkey “A”)
 - d. Select “Update Receiver”
 - e. Select correct file for programming
Note: This typically takes 3 minutes to process completely
 - f. When prompted, select “continue” button to proceed to normal working functionality

StarFire 6000™ Integrated Receiver Software Reprogramming

Note: Starfire™ 6000 Integrated Receiver software updates can be delivered by USB through the Generation 4 Display.

Preparing Starfire™ 6000 Integrated Receiver Software for a USB At Computer

1. For a StarFire™ Integrated Receiver with a Generation 4 Display, use the Software Manager Utility to download the software package to a USB.

At Machine with StarFire™ 6000 Integrated Receiver

1. Insert your USB into the Generation 4 Display with the correct file embedded and follow the steps below to initiate the programming of the StarFire™ 6000 Integrated:
 - a. Select “Software Manager”
 - b. Select “Install from USB Drive”
 - c. Select “View Updates for Other Devices”
 - d. Select “GPS Receiver”
 - e. Select correct file for programming